

# GA-6PXSVL

LGA 2011 socket motherboard for Intel® E5-1600/E5-2600 series processors

## User's Manual

Rev. 1001

## **Copyright**

© 2014 GIGA-BYTE TECHNOLOGY CO., LTD. All rights reserved.

The trademarks mentioned in this manual are legally registered to their respective owners.

## **Disclaimer**

Information in this manual is protected by copyright laws and is the property of GIGABYTE.

Changes to the specifications and features in this manual may be made by GIGABYTE without prior notice. No part of this manual may be reproduced, copied, translated, transmitted, or published in any form or by any means without GIGABYTE's prior written permission.

## **Documentation Classifications**

In order to assist in the use of this product, GIGABYTE provides the following types of documentations:

- For detailed product information, carefully read the User's Manual.

For product-related information, check on our website at:

<http://www.gigabyte.com>

# Table of Contents

Box Contents .....	5
GA-6PXSVL Motherboard Layout .....	6
GA-6PXSVL Block Diagram .....	9
Chapter 1 Hardware Installation .....	10
1-1 Installation Precautions .....	10
1-2 Product Specifications .....	11
1-3 Installing the CPU and CPU Cooler .....	13
1-3-1 Installing the CPU .....	13
1-4 Installing the Memory .....	15
1-4-1 Four Channel Memory Configuration .....	15
1-4-2 Installing a Memory .....	16
1-4-3 DIMM Population Table .....	16
1-5 Back Panel Connectors .....	17
1-6 Internal Connectors .....	18
Chapter 2 BIOS Setup .....	35
2-1 The Main Menu .....	37
2-2 Advanced Menu .....	39
2-2-1 PCI Subsystem Settings .....	40
2-2-1-1 PCI Express Settings .....	42
2-2-2 CPU Configuration .....	44
2-2-3-1 CPU Power Management Configuration .....	47
2-2-3 USB Configuration .....	49
2-2-4 SATA Configuration .....	50
2-2-5 Over Clocking Setup .....	52
2-2-6 H/W Monitor .....	53
2-2-7 Info Report Configuration .....	54
2-2-8 Super IO Configuration .....	55
2-2-9 Serial Port Console Redirection .....	57
2-2-10 Network Stack .....	60
2-2-11 Intel (R) 82574L Gigabit Network Connection .....	61
2-3 Chipset Menu .....	63
2-3-1 North Bridge .....	64
2-3-1-1 IOH Configuration .....	67
2-3-1-2 QPI Configuration .....	69
2-3-1-3 DIMM Information .....	70
2-3-2 South Bridge Configuration .....	71

2-3-3	Intel ME Subsystem.....	72
2-4	Security Menu .....	73
2-5	Boot Menu.....	74
2-5-1	CSM16 Parameters .....	76
2-5-2	CSM Parameters .....	77
2-6	Exit Menu .....	79
2-7	BIOS Recovery Instruction.....	80
Chapter 3	Appendix .....	81
3-1	Regulatory Statements.....	81




## Box Contents

- ☒ Motherboard
- ☒ Driver CD
- ☒ Two SATA cables
- ☒ I/O Shield

- The box contents above are for reference only and the actual items shall depend on the product package you obtain.  
The box contents are subject to change without notice.
- The motherboard image is for reference only.

# GA-6PXSVL Motherboard Layout




Item	Code	Description
1	U17	iTE IT8728F Super I/O
2	SYS_FAN4	System fan cable #4
3	SW_ID	ID button
4	USB3_LAN1	RJ45 LAN port (top)/USB 3.0 ports (bottom)
5	USB3_LAN2	RJ45 LAN port (top)/USB 3.0 ports (bottom)
6	VGA_COM1	COM port (top)/VGA port (bottom)
7	PS2_USB2	USB 2.0 ports (top)/PS/2 connector (bottom)
8	ATX1	24 pin power connector
9	PWR_DET1	PMBus connector
10	DDR3_P0_A0	DIMM slot (channel 1 slot 0)
11	DDR3_P0_A1	DIMM slot (channel 1 slot 1)
12	DDR3_P0_B0	DIMM slot (channel 2 slot 0)
13	DDR3_P0_B1	DIMM slot (channel 2 slot 1)
14	CPU0	Intel LGA 2011 socket
15	CPU0_FAN1	CPU fan connector
16	DDR3_P0_D1	DIMM slot (channel 4 slot 1)
17	DDR3_P0_D0	DIMM slot (channel 4 slot 0)
18	DDR3_P0_C1	DIMM slot (channel 3 slot 1)
19	DDR3_P0_C0	DIMM slot (channel 3 slot 0)
20	P1_CPU	8 pin power connector
21	SYS_FAN3	System fan #3 connector
22	SYS_FAN1	System fan #1 connector
23	SYS_FAN2	System fan #2 connector
24	SATA_SGPIO	SATA SGPIO header
25	SATA_DOM1	SATA port 1 DOM support jumper
26	U83	BIOS Upgrade ROM
27	SATA_DOM0	SATA port 0 DOM support jumper
28	SATA_0_1	SATA 6Gb/s connectors
29	SATA_2_3/SATA_4_5	SATA 3Gb/s connectors
30	BAT1	Battery socket
31	CASE_OPEN1	Chassis intrusion jumper
32	CLR_CMOS1	Clear CMOS jumper
33	PASSWORD1	Clear password jumper
34	F_PANEL1	Front panel header
35	USB_A	USB Type A connector
36	BP_1	Back plane board header
37	SATA6/7/8/9	SATA 6Gb/s connectors

38	BIOS_RCVR	BIOS Recovery jumper
39	SATA10/11/12/13	SATA 6Gb/s connectors
40	BIOS_WP	BIOS Write Protect jumper
41	F_USB3_1	USB 3.0 header
42	F_USB1	USB 2.0 header
43	COM2	Serial port cable header
44	U393	BMC Upgrade ROM
45	TPM	TPM module connector
46	LAN3_ACT	LAN3 active LED
47	U392	ASPEED AST2400VB chipset
48	BMC_LED1	BMC readiness LED
49	SSB_ME1	ME Recovery jumper
50	PCIE_SW	PCIE1 and PCIE2 bandwidth switch jumper
51	PCIE_1	PCI-E x8 slot (x8 bandwidth/Shared bandwidth with PCIE_2 slot)
52	PMBUS_SEL	PMBus Select jumper
53	BMC_FRB1	Force to Stop FRB3 Timer jumper
54	PCIE_2	PCI-E x16 slot
55	PCIE_3	PCI-E x16 slot
56	S3_MASK	S3 Power On Select jumper



**CAUTION!** If a SATA type hard drive is connected to the motherboard, please ensure the jumper is closed and set to **2-3 pins** (Default setting), in order to reduce any risk of hard disk damage. Please refer to Page 35 for SATA\_DOM0 and SATA\_DOM1 jumper setting instruction.

## GA-6PXSVL Block Diagram











# Chapter 1 Hardware Installation






## 1-1 Installation Precautions

The motherboard contains numerous delicate electronic circuits and components which can become damaged as a result of electrostatic discharge (ESD). Prior to installation, carefully read the user's manual and follow these procedures:

- Prior to installation, do not remove or break motherboard S/N (Serial Number) sticker or warranty sticker provided by your dealer. These stickers are required for warranty validation.
- Always remove the AC power by unplugging the power cord from the power outlet before installing or removing the motherboard or other hardware components.
- When connecting hardware components to the internal connectors on the motherboard, make sure they are connected tightly and securely.
- When handling the motherboard, avoid touching any metal leads or connectors.
- It is best to wear an electrostatic discharge (ESD) wrist strap when handling electronic components such as a motherboard, CPU or memory. If you do not have an ESD wrist strap, keep your hands dry and first touch a metal object to eliminate static electricity.
- Prior to installing the motherboard, please have it on top of an antistatic pad or within an electrostatic shielding container.
- Before unplugging the power supply cable from the motherboard, make sure the power supply has been turned off.
- Before turning on the power, make sure the power supply voltage has been set according to the local voltage standard.
- Before using the product, please verify that all cables and power connectors of your hardware components are connected.
- To prevent damage to the motherboard, do not allow screws to come in contact with the motherboard circuit or its components.
- Make sure there are no leftover screws or metal components placed on the motherboard or within the computer casing.
- Do not place the computer system on an uneven surface.
- Do not place the computer system in a high-temperature environment.
- Turning on the computer power during the installation process can lead to damage to system components as well as physical harm to the user.
- If you are uncertain about any installation steps or have a problem related to the use of the product, please consult a certified computer technician.

## 1-2 Product Specifications

 CPU	<ul style="list-style-type: none"> <li>Support for Intel® Xeon® E5 series processors in the LGA2011 package</li> <li>L3 cache varies with CPU</li> </ul>
 Chipset	<ul style="list-style-type: none"> <li>Intel® C602 (Patsburg) PCH</li> </ul>
 Memory	<ul style="list-style-type: none"> <li>8 x 1.5V DDR3 DIMM sockets supporting up to 64GB (UDIMM) and 256GB (RDIMM) of system memory</li> <li>Four channel memory architecture</li> <li>Support for 1600/1333/1066 memory modules</li> <li>Support for ECC memory modules</li> </ul>
 LAN	<ul style="list-style-type: none"> <li>2 x Intel® 82574 supports 10/100/1000 Mbps</li> </ul>
 Expansion Slots	<ul style="list-style-type: none"> <li>2 x PCI Express x16 slots, running at x16 (Gen3/PCIE_2/PCIE_3)</li> <li>1 x PCI Express x16 slot, running at x8 (Gen3/PCIE_2/The slot shares bandwidth with the PCIE_2 slot. When the PCIE_1 slot is populated, the PCIE_2 slot will operate at x8 mode.)</li> </ul>
 Storage Interface	<ul style="list-style-type: none"> <li>10 x SATA 6Gb/s connectors (SATA_0_1/SATA6/7/8/9/10/11/12/13)</li> <li>4 x SATA 3Gb/s connectors (SATA_2_3/SATA_4_5)</li> <li>Support for Intel RSTe SATA RAID 0, RAID 1, RAID 10, RAID 5</li> </ul>
 USB (onboard header)	<ul style="list-style-type: none"> <li>4 x USB 2.0 ports (2 via the USB brackets connected to the internal USB headers/2 at back panel)</li> <li>Up to 6 USB 3.0 ports (2 via the USB brackets connected to the internal USB headers/4 at back panel)</li> <li>1 x USB 2.0 Type A connector</li> </ul>
 Internal Connectors	<ul style="list-style-type: none"> <li>1 x 24-pin ATX main power connector</li> <li>1 x 8-pin ATX 12V power connector</li> <li>10 x SATA 6Gb/s connectors</li> <li>4 x SATA 3Gb/s connectors</li> <li>1 x CPU fan header</li> <li>4 x System fan header</li> <li>1 x Front panel header</li> <li>1 x Back plane board header</li> <li>1 x USB3.0 header</li> <li>1 x USB2.0 header</li> <li>1 x TPM header</li> <li>1 x Serial port header</li> <li>1 x PMBus header</li> <li>1 x SATA SGPIO header</li> </ul>

 Back Panel Connectors	<ul style="list-style-type: none"> <li>♦ 1 x PS/2 connector</li> <li>♦ 1 x COM port</li> <li>♦ 1 x VGA port</li> <li>♦ 2 x USB 2.0 ports</li> <li>♦ 4 x USB 3.0 ports</li> <li>♦ 2 x RJ-45 LAN ports</li> <li>♦ 1 x ID Switch button</li> </ul>
 I/O Controller	<ul style="list-style-type: none"> <li>♦ ASPEED® AST2400-VB BMC chip</li> </ul>
 Hardware Monitor	<ul style="list-style-type: none"> <li>♦ System voltage detection</li> <li>♦ CPU/System temperature detection</li> <li>♦ CPU/System/Power fan speed detection</li> <li>♦ CPU overheating warning</li> <li>♦ CPU/System/Power fan fail warning</li> <li>♦ CPU/System fan speed control</li> </ul>
 BIOS	<ul style="list-style-type: none"> <li>♦ 1 x 64 Mbit flash</li> <li>♦ AMI BIOS</li> </ul>
 Form Factor	<ul style="list-style-type: none"> <li>♦ ATX Form Factor; 12 inch x 9.6 inch</li> </ul>
* GIGABYTE reserves the right to make any changes to the product specifications and product-related information without prior notice.	



## 1-3 Installing the CPU and CPU Cooler




Read the following guidelines before you begin to install the CPU:

- Make sure that the motherboard supports the CPU.
- Always turn off the computer and unplug the power cord from the power outlet before installing the CPU to prevent hardware damage.
- Locate the pin one of the CPU. The CPU cannot be inserted if oriented incorrectly. (Or you may locate the notches on both sides of the CPU and alignment keys on the CPU socket.)
- Apply an even and thin layer of thermal grease on the surface of the CPU.
- Do not turn on the computer if the CPU cooler is not installed, otherwise overheating and damage of the CPU may occur.
- Set the CPU host frequency in accordance with the CPU specifications. It is not recommended that the system bus frequency be set beyond hardware specifications since it does not meet the standard requirements for the peripherals. If you wish to set the frequency beyond the standard specifications, please do so according to your hardware specifications including the CPU, graphics card, memory, hard drive, etc.

### 1-3-1 Installing the CPU


A. Locate the alignment keys on the motherboard CPU socket and the notches on the CPU.



B. Follow the steps below to correctly install the CPU into the motherboard CPU socket.




- Before installing the CPU, make sure to turn off the computer and unplug the power cord from the power outlet to prevent damage to the CPU.
- To protect the socket contacts, do not remove the protective plastic cover unless the CPU is inserted into the CPU socket. Save the cover properly and replace it if the CPU is removed.




Step 1:

Push the lever closest to the "unlock" marking "☐" (below referred as lever A) down and away from the socket to release it.



Step 2:

Push the lever closest to the "lock" marking "☐" (below referred as lever B) down and away from the socket. Then lift the lever.




Step 3:

Gently press lever A to allow the load plate to rise. Open the load plate. (Note: DO NOT touch the socket contacts after the load plate is opened.)



Step 4:

Hold the CPU with your thumb and index fingers. Align the CPU pin one marking (triangle) with the pin one corner of the CPU socket (or align the CPU notches with the socket alignment keys) and carefully insert the CPU into the socket vertically.



Step 5:

Once the CPU is properly inserted, carefully replace the load plate. Then secure lever B under its retention tab. The protective plastic cover may pop off from the load plate during the process of engaging the lever. Remove the cover. Save the cover properly and always replace it when the CPU is not installed.



Step 6:

Finally, secure lever A under its retention tab to complete the installation of the CPU.

## 1-4 Installing the Memory



Read the following guidelines before you begin to install the memory:

- Make sure that the motherboard supports the memory. It is recommended that memory of the same capacity, brand, speed, and chips be used.
- Always turn off the computer and unplug the power cord from the power outlet before installing the memory to prevent hardware damage.
- Memory modules have a foolproof design. A memory module can be installed in only one direction. If you are unable to insert the memory, switch the direction.

### 1-4-1 Four Channel Memory Configuration

This motherboard provides eight DDR3 memory sockets and supports Four Channel Technology. After the memory is installed, the BIOS will automatically detect the specifications and capacity of the memory. Enabling Four Channel memory mode will double the original memory bandwidth.


The eight DDR3 memory sockets are divided into four channels and each channel has two memory sockets as following:

Channel 1: DDR3\_P0\_A0, DDR3\_P0\_A1

Channel 2: DDR3\_P0\_B0, DDR3\_P0\_B1

Channel 3: DDR3\_P0\_C0, DDR3\_P0\_C1


Channel 4: DDR3\_P0\_D0, DDR3\_P0\_D1



Due to CPU limitations, read the following guidelines before installing the memory in Four Channel mode.


1. Four Channel mode cannot be enabled if only one DDR3 memory module is installed.
2. When enabling Four Channel mode with two or four memory modules, it is recommended that memory of the same capacity, brand, speed, and chips be used for optimum performance.

### 1-4-2 Installing a Memory

 Before installing a memory module, make sure to turn off the computer and unplug the power cord from the power outlet to prevent damage to the memory module.  
Be sure to install DDR3 DIMMs on this motherboard.

**Installation Step:**

- Step 1. Insert the DIMM memory module vertically into the DIMM slot, and push it down.  
Step 2. Close the plastic clip at both edges of the DIMM slots to lock the DIMM module.  
Note: For dual-channel and four-channel operation, DIMMs must be installed in matched pairs.  
Step 3. Reverse the installation steps when you wish to remove the DIMM module.




### 1-4-3 DIMM Population Table

R-DIMM	1N or 2N	DIMM1	DIMM0
	1N	Empty	Single-Rank
	1N	Empty	Dual-Rank
	1N	Empty	Quad-Rank
	1N	Single-Rank	Single-Rank
	1N	Single-Rank	Dual-Rank
	1N	Dual-Rank	Dual-Rank
	1N	Single-Rank	Quad-Rank
	1N	Dual-Rank	Quad-Rank
	1N	Quad-Rank	Quad-Rank

U-DIMM	1N or 2N	DIMM1	DIMM0
	1N	Empty	Single-Rank
	1N	Empty	Dual-Rank
	2N	Single-Rank	Single-Rank
	2N	Single-Rank	Dual-Rank
	2N	Dual-Rank	Dual-Rank

# 1-5 Back Panel Connectors



## a USB 2.0 Port

The USB port supports the USB 2.0 specification. Use this port for USB devices such as a USB keyboard/mouse, USB printer, USB flash drive and etc.

## b PS/2 Keyboard/Mouse Port

Connect a PS/2 keyboard or mouse to this port.

## c Serial Port

Connects to serial-based mouse or data processing devices.

## d Video Port

The video in port allows connect to video in, which can also apply to video loop thru function.

## e RJ-45 LAN Port


The Gigabit Ethernet LAN port provides Internet connection at up to 1 Gbps data rate. The following describes the states of the LAN port LEDs.

## f USB 3.0 Port

The USB port supports the USB 3.0 specification. Use this port for USB devices such as a USB keyboard/mouse, USB printer, USB flash drive and etc.

## g ID Switch Button

This button provide the selected unit identification function.



82574 Speed LED:

State	Description
Yellow On	1 Gbps data rate
Yellow Blink	Identify 1 Gbps data rate
Green On	100 Mbps data rate
Green Blink	Identify 100 Mbps data rate
Off	10 Mbps data rate


Link/Activity LED:

State	Description
On	Link between system and network or no access
Blinking	Data transmission or receiving is occurring
Off	No data transmission or receiving is occurring



- When removing the cable connected to a back panel connector, first remove the cable from your device and then remove it from the motherboard.
- When removing the cable, pull it straight out from the connector. Do not rock it side to side to prevent an electrical short inside the cable connector.

## 1-6 Internal Connectors



1) ATX1	18) COM2
2) P1_CPU	19) LAN3_ACT
3) CPU_FAN1 (CPU Fan)	20) BMC_LED1
4) SYS_FAN1 (System Fan)	21) SATA_SGPIO
5) SYS_FAN3 (System Fan)	22) BAT1
6) SYS_FAN2 (System Fan)	23) CLR_CMOS1
7) SYS_FAN4 (System Fan)	24) PASSWORD1
8) PWR_DET1 (PMBus)	25) CASE_OPEN1
9) SATA0_1	26) BIOS_RCVR
10) SATA_2_3/SATA_4_5	27) SSB_ME1
11) SATA6/7/8/9	28) PMBUS_SEL
12) SATA10/11/12/13	29) BMC_FRB1
13) TPM	30) PCIE_SW
14) F_PANEL1	31) BIOS_WP
15) BP_1	32) S3_MASK
16) F_USB3_1	33) SATA_DOM0
17) F_USB1	34) SATA_DOM1



Read the following guidelines before connecting external devices:


- First make sure your devices are compliant with the connectors you wish to connect.
- Before installing the devices, be sure to turn off the devices and your computer. Unplug the power cord from the power outlet to prevent damage to the devices.
- After installing the device and before turning on the computer, make sure the device cable has been securely attached to the connector on the motherboard.

## 1/2) ATX1/P1\_CPU (2x12 Main Power Connector and 2x4 12V Power Connector)


With the use of the power connector, the power supply can supply enough stable power to all the components on the motherboard. Before connecting the power connector, first make sure the power supply is turned off and all devices are properly installed. The power connector possesses a foolproof design. Connect the power supply cable to the power connector in the correct orientation. The 12V power connector mainly supplies power to the CPU. If the 12V power connector is not connected, the computer will not start.



To meet expansion requirements, it is recommended that a power supply that can withstand high power consumption be used (500W or greater). If a power supply is used that does not provide the required power, the result can lead to an unstable or unbootable system.




P1\_CPU



Pin No.	Definition
1	GND
2	GND
3	GND
4	GND
5	+12V
6	+12V
7	+12V
8	+12V

ATX1





Pin No.	Definition	Pin No.	Definition
1	3.3V	13	3.3V
2	3.3V	14	-12V
3	GND	15	GND
4	+5V	16	PS_ON
5	GND	17	GND
6	+5V	18	GND
7	GND	19	GND
8	Power Good	20	-5V
9	5VSB (stand by +5V)	21	+5V
10	+12V	22	+5V
11	+12V	23	+5V
12	3.3V	24	GND



### 3/4/5/6/7) CPU\_FAN1/SYS\_FAN1/SYS\_FAN2/SYS\_FAN3/SYS\_FAN4

#### (CPU Fan/System Fan Headers)

The motherboard has a 4-pin CPU fan header (CPU\_FAN1), four 4-pin (SYS\_FAN1/SYS\_FAN2/SYS\_FAN3) system fan headers. Most fan headers possess a foolproof insertion design. When connecting a fan cable, be sure to connect it in the correct orientation (the black connector wire is the ground wire). The motherboard supports CPU fan speed control, which requires the use of a CPU fan with fan speed control design. For optimum heat dissipation, it is recommended that a system fan be installed inside the chassis.




Pin No.	Definition
1	GND
2	+12V
3	Sense
4	Speed Control



- Be sure to connect fan cables to the fan headers to prevent your CPU and system from overheating. Overheating may result in damage to the CPU or the system may hang.
- These fan headers are not configuration jumper blocks. Do not place a jumper cap on the headers.



### 8) PWR\_DET1 (PMBus connector)



Pin No.	Definition
1	SMB CLK
2	SMB DATA
3	SMB Alert
4	GND
5	3.3V Sense

## 9) SATA0\_1 (SATA 6Gb/s Connectors)

The SATA connectors conform to SATA 6Gb/s standard and are compatible with SATA 3Gb/s and 1.5Gb/s standard. Each SATA connector supports a single SATA device.



When SATA\_DOM0/1 jumper are set to 2-3 pin:


Pin No.	Definition
1	GND
2	TXP
3	TXN
4	GND
5	RXN
6	RXP
7	GND

When SATA\_DOM0/1 jumper are set to 1-2 pin:

Pin No.	Definition
1	GND
2	TXP
3	TXN
4	GND
5	RXN
6	RXP
7	P5V

## 10) SATA\_2\_3/SATA\_4\_5 (SATA 3Gb/s Connectors)

The SATA connectors conform to SATA 3Gb/s standard and are compatible with SATA 1.5Gb/s standard. Each SATA connector supports a single SATA device.



Pin No.	Definition
1	GND
2	TXP
3	TXN
4	GND
5	RXN
6	RXP
7	GND





- A RAID 0 or RAID 1 configuration requires at least two hard drives. If more than two hard drives are configured, the total number of hard drives must be an even number.
- A RAID 10 configuration requires four hard drives.

(Note) When a RAID configuration is built across the SATA 6Gb/s channels, the system performance of the RAID configuration may vary depends on the devices are connected.


## 11/12) SATA6/7/8/9/11/12/13 (SATA 6Gb/s Connectors)

The SATA connectors conform to SATA 6Gb/s standard and are compatible with SATA 3Gb/s and 1.5Gb/s standard. Each SATA connector supports a single SATA device.



Pin No.	Definition
1	GND
2	TXP
3	TXN
4	GND
5	RXN
6	RXP
7	GND

## 13) TPM (TPM Module connector)




14 13



Pin No.	Definition	Pin No.	Definition
1	CLK_33M_TPM	8	TPM_DET_N
2	P_3V3_AUX	9	LPC_LAD2
3	RST_TPM	10	NC
4	P3V3	11	LPC_LAD3
5	LPC_LAD0	12	GND
6	LPC_SERIRQ	13	LPC_LFRAME_N
7	LPC_LAD1	14	GND

#### 14) F\_PANEL1 (Front Panel Header)

Connect the power switch, reset switch, chassis intrusion switch/sensor and system status indicator on the chassis to this header according to the pin assignments below. Note the positive and negative pins before connecting the cables.




Pin No.	Signal Name	Definition
1	PWLED+	Power LED Signal anode (+)
2	5VSB	5V Standby Power
3	NC	No Pin
4	ID_LED+	ID LED Signal anode (+)
5	PWLED-	Power LED Signal cathode(-)
6	ID_LED-	ID LED Signal cathode(-)
7	HD+	Hard Disk LED Signal anode (+)
8	F_SYSRDY	System Front board LED Signal
9	HD-	Hard Disk LED Signal cathode(-)
10	SYS_STATUS-	System Status LED Signal cathode(-)
11	PWB+	Power Button Signal anode (+)
12	L1_ACT	LAN1 active LED Signal
13	PWB+_GND	Ground
14	L1_LINK-	LAN1 Link LED Signal cathode(-)
15	RST_BTN+	Reset button Signal anode (+)
16	SENSOR_SDA	SMBus Data Signal
17	RST_BTN_GND	Ground
18	SENSOR_SCL	SMBus Clock Signal
19	ID_SW+	ID Switch Signal anode (+)
20	CASE_OPEN-	Chassis intrusion Signal cathode(-)
21	ID_SW (GND)	Ground
22	L2_ACT	LAN2 active LED Signal
23	NMI_SW-	NMI switch Signal cathode(-)
24	L2_LINK-	LAN2 Link LED Signal cathode(-)




The front panel design may differ by chassis. A front panel module mainly consists of power switch, reset switch, power LED, hard drive activity LED, speaker and etc. When connecting your chassis front panel module to this header, make sure the wire assignments and the pin assignments are matched correctly.

15) BP\_1 (HDD Back Plane Board Headers)



## 16) F\_USB3\_1 (USB 3.0 Header)


The headers conform to USB 3.0 specification. Each USB header can provide two USB ports via an optional USB bracket. For purchasing the optional USB bracket, please contact the local dealer.



Pin No.	Definition
1	Power
2	IntA_P1_SSRX-
3	IntA_P1_SSRX+
4	GND
5	IntA_P1_SSTX-
6	IntA_P1_SSTX+
7	GND
8	IntA_P1_D-
9	IntA_P1_D+
10	NC
11	IntA_P2_D+
12	IntA_P2_D-
13	GND
14	IntA_P2_SSTX+
15	IntA_P2_SSTX-
16	GND
17	IntA_P2_SSRX+
18	IntA_P2_SSRX-
19	Power
20	No Pin

## 17) F\_USB1 (Front USB Header)



The headers conform to USB 2.0 specification. Each USB header can provide two USB ports via an optional USB bracket. For purchasing the optional USB bracket, please contact the local dealer.



Pin No.	Definition
1	Power (5V)
2	Power (5V)
3	USB DX-
4	USB DY-
5	USB DX+
6	USB DY+
7	GND
8	GND
9	No Pin
10	NC


18) COM2 (Serial Port Header)

The COM header can provide one serial port via an optional COM port cable. For purchasing the optional COM port cable, please contact the local dealer.




Pin No.	Definition
1	NDCD-
2	NDSR-
3	NSIN
4	NRST-
5	NSOUT
6	NCTS-
7	NDTR-
8	NR!
9	GND
10	No Pin

19) LAN3\_ACT (LAN3 link/active LED header)



Pin No.	Definition
1	3.3V
2	Active


20) BMC\_LED1 (BMC Firmware Readiness LED)



State	Description
On	BMC firmware is initial
Blinking	BMC firmware is ready
Off	System is powered off

21) SATA\_SGPIO (SATA SGPIO Header)

SGPIO stands for Serial General Purpose Input/Output which is a 4-signal (or 4-wire) bus used between a Host Bus Adapter (HBA) and a backplane. Out of the 4 signals, 3 are driven by the HBA and 1 is driven by the backplane. Typically, the HBA is a storage controller located inside a server, desktop, rack or workstation computer that interfaces with Hard disk drives (HDDs) to store and retrieve data. This header provides the SATA interface of SGPIO funtion.





Pin No.	Definition
1	SGPIO_SATA_DATAIN
2	No Pin
3	SGPIO_SATA_DATAOUT
4	GND
5	GND
6	SGPIO_SATA_LOAD
7	NC
8	SGPIO_SATA_CLOCK



## 22) BAT1 (Battery)


The battery provides power to keep the values (such as BIOS configurations, date, and time information) in the CMOS when the computer is turned off. Replace the battery when the battery voltage drops to a low level, or the CMOS values may not be accurate or may be lost.



- Always turn off your computer and unplug the power cord before replacing the battery.
- Replace the battery with an equivalent one. Danger of explosion if the battery is replaced with an incorrect model.
- Contact the place of purchase or local dealer if you are not able to replace the battery by yourself or uncertain about the battery model.
- When installing the battery, note the orientation of the positive side (+) and the negative side (-) of the battery (the positive side should face up).
- Used batteries must be handled in accordance with local environmental regulations.

## 23) CLR\_CMOS1 (Clearing CMOS Jumper)

Use this jumper to clear the CMOS values (e.g. date information and BIOS configurations) and reset the CMOS values to factory defaults. To clear the CMOS values, place a jumper cap on the two pins to temporarily short the two pins or use a metal object like a screwdriver to touch the two pins for a few seconds.




1 - 1-2 Close: Normal operation (Default setting)


1 - 2-3 Close: Clear CMOS data



- Always turn off your computer and unplug the power cord from the power outlet before clearing the CMOS values.
- After clearing the CMOS values and before turning on your computer, be sure to remove the jumper cap from the jumper. Failure to do so may cause damage to the motherboard.
- After system restart, go to BIOS Setup Exit menu and load factory defaults (select **Restore Defaults**) or manually configure the BIOS settings (refer to Chapter 2, "BIOS Setup," for BIOS configurations).


## 24) PASSWORD1 (Clearing Supervisor Password Jumper)





1  1-2 Close: Normal operation. (Default setting)

1  2-3 Close: Clear supervisor password.


## 25) CASE\_OPEN1 (Case open intrusion header)





 Open: Active chassis intrusion alert.


 Closed: Normal operation.



## 26) BIOS\_RCVR (BIOS Recovery Jumper)




- 1  1-2 Close: Normal operation. (Default setting)
- 1  2-3 Close: BIOS recovery mode.



## 27) SSB\_ME1 (ME Recovery Jumper)




- 1  1-2 Close: Enable ME recovery.
- 1  2-3 Close: Disable ME recovery. (Default setting)



### 28) PMBUS\_SEL (PMBus Power Select Jumper)




- 1  1-2 Close: PMBus connects to PCH.
- 1  2-3 Close: PMBus connects to BMC. (Default setting)


### 29) BMC\_FRB1 (Force to Stop FRB3 Timer Jumper)




- 1  1-2 Close: Normal operation. (Default setting)
- 1  2-3 Close: Force to Stop FRB3 Timer.


### 30) PCIE\_SW (PCIE\_1 and PCIE\_2 bandwidth switch Jumper)





1  1-2 Close: PCIE\_2 operates in x16 bandwidth.  
(Default setting)

1  2-3 Close: PCIE\_2 operates in x8 bandwidth.


### 31) BIOS\_WP (BIOS Write Protect Jumper)





1  1-2 Close: Normal operation. (Default setting)

1  2-3 Close: Enable BIOS write protect function.

### 32) S3\_MASK (S3 Power On Select Jumper)



- 1  1-2 Close: Stop an initial power on when BMC is not ready.
- 1  2-3 Close: Keep initial power on. (Default setting)


### 33/34) SATA\_DOM0/SATA\_DOM1 (SATA port 0 and port 1 DOM Jumpers)



#### CAUTION!

- If the SATA DOM power is supplied by the motherboard, set the jumper to pin 1-2.
- If the SATA DOM power is supplied by external power, set the jumper to pin 2-3.
- If a SATA type hard drive is connected to the motherboard, please ensure the jumper is closed and set to **2-3 pins** (Default setting), in order to reduce any risk of hard disk damage.

Please refer to the pin definition table in the following.



For SATA\_DOM0

Pin No.	Definition
1	P5V
2	SATA_DOM_0
3	GND

For SATA\_DOM1

Pin No.	Definition
1	P5V
2	SATA_DOM_1
3	GND

## Chapter 2 BIOS Setup

BIOS (Basic Input and Output System) records hardware parameters of the system in the EFI on the motherboard. Its major functions include conducting the Power-On Self-Test (POST) during system startup, saving system parameters and loading operating system, etc. BIOS includes a BIOS Setup program that allows the user to modify basic system configuration settings or to activate certain system features. When the power is turned off, the battery on the motherboard supplies the necessary power to the CMOS to keep the configuration values in the CMOS.

To access the BIOS Setup program, press the <F2> key during the POST when the power is turned on.



- BIOS flashing is potentially risky, if you do not encounter problems of using the current BIOS version, it is recommended that you don't flash the BIOS. To flash the BIOS, do it with caution. Inadequate BIOS flashing may result in system malfunction.
- It is recommended that you not alter the default settings (unless you need to) to prevent system instability or other unexpected results. Inadequately altering the settings may result in system's failure to boot. If this occurs, try to clear the CMOS values and reset the board to default values. (Refer to the "Restore Defaults" section in this chapter or introductions of the battery/clearing CMOS jumper in Chapter 1 for how to clear the CMOS values.)

### BIOS Setup Program Function Keys

<<-><->>	Move the selection bar to select the screen
<↑><↓>	Move the selection bar to select an item
<Enter>	Execute command or enter the submenu
<+>	Increase the numeric value or make changes
<->	Decrease the numeric value or make changes
<Esc>	Main Menu: Exit the BIOS Setup program Submenus: Exit current submenu
<F1>	Show descriptions of general help
<F3>	Restore the previous BIOS settings for the current submenus
<F9>	Load the Optimized BIOS default settings for the current submenus
<F10>	Save all the changes and exit the BIOS Setup program

■ **Main**

This setup page includes all the items in standard compatible BIOS.

■ **Advanced**

This setup page includes all the items of BIOS special enhanced features.

(ex: Auto detect fan and temperature status, automatically configure hard disk parameters.)

■ **Chipset**

This setup page includes all the submenu options for configuring the function of North Bridge and South Bridge.

(ex: Auto detect fan and temperature status, automatically configure hard disk parameters.)

■ **Security**

Change, set, or disable supervisor and user password. Configuration supervisor password allows you to restrict access to the system and BIOS Setup.

A supervisor password allows you to make changes in BIOS Setup.

A user password only allows you to view the BIOS settings but not to make changes.

■ **Boot**

This setup page provides items for configuration of boot sequence.

■ **Exit**

Save all the changes made in the BIOS Setup program to the CMOS and exit BIOS Setup. (Pressing <F10> can also carry out this task.)

Abandon all changes and the previous settings remain in effect. Pressing <Y> to the confirmation message will exit BIOS Setup. (Pressing <Esc> can also carry out this task.)



## 2-1 The Main Menu

Once you enter the BIOS Setup program, the Main Menu (as shown below) appears on the screen. Use arrow keys to move among the items and press <Enter> to accept or enter other sub-menu.

### Main Menu Help


The on-screen description of a highlighted setup option is displayed on the bottom line of the Main Menu.

### Submenu Help

While in a submenu, press <F1> to display a help screen (General Help) of function keys available for the menu. Press <Esc> to exit the help screen. Help for each item is in the Item Help block on the right side of the submenu.



- When the system is not stable as usual, select the **Restore Defaults** item to set your system to its defaults.
- The BIOS Setup menus described in this chapter are for reference only and may differ by BIOS version.



☞ **BIOS Information**

☞ **Project Version**

Display version number of the project.

☞ **BIOS Build Date and Time**

Displays the date and time when the BIOS setup utility was created.

☞ **EC Firmware Version**

Display version number of the Firmware setup utility.

☞ **Processor Information**

☞ **CPU Type/ Max CPU Speed/ CPU Signature / Processor Cores / Microcode Patch**

Displays the technical specifications for the installed processor.

☞ **Memory Information**

☞ **Total Memory / Current Memory Speed**

Displays the technical specifications for the installed memory.

☞ **System Date**


Set the date following the weekday-month-day- year format.

☞ **System Time**


Set the system time following the hour-minute- second format.

## 2-2 Advanced Menu

The Advanced menu display submenu options for configuring the function of various hardware components. Select a submenu item, then press Enter to access the related submenu screen.



## 2-2-1 PCI Subsystem Settings



### PCI Express Slot #1/2/3 I/O ROM

When enabled, This setting will initialize the device expansion ROM for the related PCI-E slot.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### Onboard LAN #1/2 Controller

Enable/Disable Onboard LAN controllers.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### Onboard LAN I/O ROM Option

Configure onboard LAN devices and initialize device expansion ROM.

Options available: PXE/iSCSI. Default setting is **PXE**.

### Onboard LAN1/2 I/O ROM

Enable/Disable onboard LAN devices and initialize device expansion ROM.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### PCI 64bit Resources Handling

### Above 4G Decoding

Enable/Disable Above 4G Decoding.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### PCI Common Settings

### PCI Latency Timer

Configure PCI Latency Timer.

Options available: 32 PCI Bus Clocks/64 PCI Bus Clocks/96 PCI Bus Clocks/128 PCI Bus Clocks/160 PCI Bus Clocks/192 PCI Bus Clocks/224 PCI Bus Clocks/248 PCI Bus Clocks.

Default setting is **32 PCI Bus Clocks**.

### ☞ **VGA Platte Snoop**

Enable/Disable VGA Palette Registers Snooping.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### ☞ **PERR Generation**

When this item is set to enabled, PCI bus parity error (PERR) is generated and is routed to NMI.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### ☞ **SERR Generation**


When this item is set to enabled, PCI bus system error (SERR) is generated and is routed to NMI.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### ☞ **PCI Express Settings**

Press [Enter] for configuration of advanced items.

## 2-2-1-1 PCI Express Settings



### ☞ PCI Express Device Register Settings

#### ☞ Relaxed Ordering

Enable/Disable PCI Express Device Relaxed Ordering feature.

Options available: Enabled/Disabled. Default setting is **Disabled**.

#### ☞ Extended Tag

When this feature is enabled, the system will allow device to use 8-bit Tag field as a requester.

Options available: Enabled/Disabled. Default setting is **Disabled**.

#### ☞ No Snoop

Enable/Disable PCI Express Device No Snoop option.

Options available: Enabled/Disabled. Default setting is **Enabled**.

#### ☞ Maximum Payload

Set maximum payload for PCI Express Device or allow system BIOS to select the value.

Options available: Auto/128 Bytes/256 Bytes/512 Bytes/1024 Bytes/2048 Bytes/4096 Bytes.

Default setting is **Auto**.

#### ☞ Maximum Read Request

Set maximum Read Request size for PCI Express Device or allow system BIOS to select the value.

Options available: Auto/128 Bytes/256 Bytes/512 Bytes/1024 Bytes/2048 Bytes/4096 Bytes.

Default setting is **Auto**.

#### ☞ Extended Synch

When this feature is enabled, the system will allow generation of Extended Synchronization patterns.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### **Link Training Retry**

Define the number of Retry Attempts software will take to retrain the link if previous training attempt was unsuccessful. Press <+> / <-> keys to increase or decrease the desired values.

### **Link Training Timeout (us)**



Define the number of Microseconds software will wait before polling 'Link Training' bit in Link Status register. Press <+> / <-> keys to increase or decrease the desired values. Value range is from 10 to 10000 us.

### **Unpopulated Links**

When this item is set to 'Disable Link', the system will operate power save feature for those unpopulated PCI Express links.

Options available: Keep Link ON/ Disable. Default setting is **Keep Link ON**.

## 2-2-2 CPU Configuration





## ☞ CPU Information

### ☞ Socket 0 CPU Information

### ☞ CPU Type/ Signature / Microcode Patch / Max CPU Speed / Min CPU Speed / Processor Cores / Intel HT Technology / Intel VT-x Technology

Displays the technical specifications for the installed processor.

### ☞ Intel HT Technology / Intel VT-x Technology

Displays the support information for the installed processor.

## ☞ Cache Information

### ☞ L1 Data Cache / L1 Code Cache / L2 Cache / L3 Cache

Displays the technical specifications for the installed processor.

### ☞ CPU Speed / 64-bit

## ☞ Hyper Threading

The Intel Hyper Threading Technology allows a single processor to execute two or more separate threads concurrently. When hyper-threading is enabled, multi-threaded software applications can execute their threads, thereby improving performance.

Options available: Enabled/Disabled. Default setting is **Enabled**.

## ☞ Active Processor Cores <sup>(Note)</sup>

Allows you to determine whether to enable all CPU cores.

Options available: All/1/2/3. Default setting is **All**.

## ☞ Limit CPUID Maximum

When enabled, the processor will limit the maximum CPUID input values to 03h when queried, even if the processor supports a higher CPUID input value.

When disabled, the processor will return the actual maximum CPUID input value of the processor when queried.

Options available: Enabled/Disabled. Default setting is **Disabled**.

## ☞ Execute Disable Bit

When enabled, the processor prevents the execution of code in data-only memory pages. This provides some protection against buffer overflow attacks.

When disabled, the processor will not restrict code execution in any memory area. This makes the processor more vulnerable to buffer overflow attacks.

Options available: Enabled/Disabled. Default setting is **Enabled**.

## ☞ Hardware Prefetcher

Select whether to enable the speculative prefetch unit of the processor.

Options available: Enabled/Disabled. Default setting is **Enabled**.

## ☞ Adjacent Cache Line Prefetch

When enabled, cache lines are fetched in pairs. When disabled, only the required cache line is fetched.

Options available: Enabled/Disabled. Default setting is **Enabled**.

(Note) This item is present only if you install a CPU that supports this feature. For more information about Intel CPUs' unique features, please visit Intel's website.

☞ **DCU Streamer Prefetch**

Enable prefetch of next L1 Data line based upon multiple loads in same cache line.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **DCU IP Prefetcher**

Enable prefetch of next L1 Data line based upon sequential load history.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Intel Virtualization Technology**


Select whether to enable the Intel Virtualization Technology function. VT allows a single platform to run multiple operating systems in independent partitions.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **CPU Power Management Configuration**

Press [Enter] for configuration of advanced items.

## 2-2-3-1 CPU Power Management Configuration



### ☞ CPU Power Management Configuration

#### ☞ Power Technology

Configure the power management features.

Options available: Disable/Energy Efficient/Custom. Default setting is **Custom**.

#### ☞ EIST (Enhanced Intel SpeedStep Technology)

Conventional Intel SpeedStep Technology switches both voltage and frequency in tandem between high and low levels in response to processor load.

Options available: Enabled/Disabled. Default setting is **Enabled**.

#### ☞ Turbo Mode

When this item is enabled, the processor will automatically ramp up the clock speed of 1-2 of its processing cores to improve its performance.

When this item is disabled, the processor will not overclock any of its core.

Options available: Enabled/Disabled. Default setting is **Enabled**.

#### ☞ P-STATE Coordination

In HW\_ALL mode, the processor hardware is responsible for coordinating the P-state among logical processors dependencies. The OS is responsible for keeping the P-state request up to date on all logical processors.

In SW\_ALL mode, the OS Power Manager is responsible for coordinating the P-state among logical processors with dependencies and must initiate the transition on all of those Logical Processors.

In SW\_ANY mode, the OS Power Manager is responsible for coordinating the P-state among logical processors with dependencies and may initiate the transition on any of those Logical Processors.

Options available: HW\_ALL/SW\_ALL/SW\_ANY. Default setting is **HW\_ALL**.

☞ **CPU C3/C6 Report** <sup>(Note)</sup>

Allows you to determine whether to let the CPU enter C3/C6 mode in system halt state. When enabled, the CPU core frequency and voltage will be reduced during system halt state to decrease power consumption. The C3/C6 state is a more enhanced power-saving state than C1.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Package C State Limit**

Configure state for the C-State package limit.

Options available: C0/C1/C6/C7/No Limit. Default setting is **No Limit**.

☞ **Energy Performance**

Energy Performance Bias is Intel CPU function.

The larger value in MSR\_ENERGY\_PERFORMANCE\_BIAS register, CPU will save more power but lose more performance.

**Note:** This register will be changed by OS too if OS support it like Windows 2008 or newer Linux.

Options available:

Performance : Write value 0 into MSR\_ENERGY\_PERFORMANCE\_BIAS

Balanced Performance: Write value 7 into MSR\_ENERGY\_PERFORMANCE\_BIAS

Balanced Energy: Write value 11 into MSR\_ENERGY\_PERFORMANCE\_BIAS

Energy Efficient: Write value 15 into MSR\_ENERGY\_PERFORMANCE\_BIAS

Default setting is **Performance**.

(Note) This item is present only if you install a CPU that supports this feature. For more information about Intel CPUs' unique features, please visit Intel's website.

## 2-2-3 USB Configuration



### ☞ USB Configuration

### ☞ USB Module Version

Display USB module version information.

### ☞ Legacy USB Support

Enables or disables support for legacy USB devices.

Options available: Auto/Enabled/Disabled. Default setting is **Enabled**.

### ☞ USB3.0 Support

Enables or disables onboard USB 3.0 devices.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### ☞ XHCI Hand-off

Enable/Disable XHCI (USB 3.0) Hand-off function.



Options available: Enabled/Disabled. Default setting is **Enabled**.

### ☞ EHCI Hand-off

Enable/Disable EHCI (USB 2.0) Hand-off function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

## 2-2-4 SATA Configuration



## ☞ SATA Configuration

### ☞ SATA Port 0/1/2/3/4/5

Displays the installed HDD devices information. System will automatically detect HDD type.

### ☞ SATA Mode Selection

Select the on chip SATA type.

RAID Mode: When set to RAID, the SATA controller enables both its RAID and AHCI functions. You will be allows access the RAID setup utility at boot time.

AHCI Mode: When set to AHCI, the SATA controller enables its AHCI functionality. Then the RAID function is disabled and cannot be access the RAID setup utility at boot time.

Options available: RAID/AHCI/Disabled. Default setting is **AHCI Mode**.

### ☞ Aggressive Link Power Management

Enable PCH to aggressively enter link power state.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### ☞ Hot Plug (for Serial SATA Port 0/1/2/3/4/5)

Enable/Disable Hot Plug support for Serial ATA Port 0/1/2/3/4/5.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### ☞ External SATA (for Serial SATA Port 0/1/2/3/4/5)

Enable/Disable External SATA support for Serial ATA Port 0/1/2/3/4/5.

Options available: Enabled/Disabled. Default setting is **Disabled**.

Options available: Hard Disk Drive/Solid State Drive. Default setting is **Disabled**.



### ☞ Straggered Spin Up (for Serial SATA Port 0/1/2/3/4/5)

On an edge detect from 0 to 1, the PCH starts a COMreset initialization to the device.

Options available: Enabled/Disabled. Default setting is **Disabled**.



1. With configuration for SATA port 6~13, press press <Ctrl>+<M> to enter the setup menu.
2. The following screens appear, and you can start up the configuration for SATA port 6~13.



## 2-2-5 Over Clocking Setup



### Over Clocking Setup

#### Vcore voltage/Vsa voltage/Eval Cpu Freq/TSC measured Bclk Freq/Eval DDR Date Rate

Displays a real-time record of the system related voltage information. These items on this window are non-configurable.

#### ClockGen BCLK Adjust

Options available: BCLK offset +0MHz (0 Step)/BCLK offset +1MHz (10 Step)/  
BCLK offset +2MHz (20 Step)/BCLK offset +30MHz (30 Step)/BCLK offset +40MHz (40 Step)/  
BCLK offset +50MHz (50 Step). Default setting is **BCLK offset +0MHz (0 Step)**.

#### Gear Ratio

Options available: X 1.0/ x 1.25/ x 1.67. Default setting is **x 1.0**.

#### Enable Vcore override

Options available: Enabled/Disabled. Default setting is **Disabled**.

#### Enable Vsa override

Options available: Enabled/Disabled. Default setting is **Disabled**.

#### DDR Vdd override

Options available: Enabled/Disabled. Default setting is **Disabled**.


#### XMP Profile

Options available: Enabled/Disabled. Default setting is **Disabled**.



## 2-2-6 H/W Monitor

Press Enter to view the Hardware Monitor screen which displays a real-time record of the CPU/system temperature, and fan speed, Items on this window are non-configurable.



## 2-2-7 Info Report Configuration



### Info Report Configuration

#### Post Report

#### Post Report

Enable/Disable Post Report support.

Options available: Enabled/Disabled. Default setting is **Enabled**.


#### Error Message Report

#### Info Error Message

Enable/Disable Info Error Message support.

Options available: Enabled/Disabled. Default setting is **Enabled**.

## 2-2-8 Super IO Configuration





## 🔑 Super IO Configuration

### 🔑 Super IO Chip

Display the model name of Super IO chipset.

### 🔑 Serial Port 0/1 Configuration

#### 🔑 Serial Port

When enabled allows you to configure the serial port settings. When set to Disabled, displays no configuration for the serial port.

Options available: Enabled/Disabled. Default setting is **Enabled**.

#### 🔑 Device Settings

Displays the Serial Port base I/O address and IRQ.

#### 🔑 Change Settings

Change Serial Port 0/1 device settings. When set to Auto allows the server's BIOS or OS to select a configuration.

Options available: Auto/IO=3F8; IRQ=4/IO=3F8h; IRQ=3,4,5,6,7,10,11,12/

IO=2F8h; IRQ=3,4,5,6,7,10,11,12 /IO=3E8h; IRQ=3,4,5,6,7,10,11,12/IO=2E8h; IRQ=3,4,5,6,7,10,11,12.

## 2-2-9 Serial Port Console Redirection

Bios Setup Utility		
Advanced		
COM1		Console Redirection Enable or Disable.
Console Redirection	[Enabled]	
▶ Console Redirection Settings		
COM2		
Console Redirection	[Enabled]	
▶ Console Redirection Settings		
Serial Port for Out-of-Band Management/ Windows Emergency Management Services (EMS)		
Console Redirection	[Enabled]	
▶ Console Redirection Settings		
SDL Switch	[Disabled]	
		++: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit

Bios Setup Utility		
Advanced		
COM1		Emulation: ANSI: Extended ASCII char set. VT100: ASCII char set. VT100+: Extends VT100 to support color, function keys, etc. VT-UTF8: Uses UTF8 encoding to map Unicode chars onto 1 or more bytes.
Console Redirection Settings		
Terminal Type	[ANSI]	
Bits per second	[115200]	
Data Bits	[8]	
Parity	[None]	
Stop Bits	[1]	
Flow Control	[None]	
VT-UTF8 Combo Key Support	[Enabled]	
Recorder Mode	[Disabled]	
Resolution 100x31	[Enabled]	
Legacy OS Redirection Resolution	[80x24]	
Putty KeyPad	[VT100]	
Redirection After BIOS POST	[Always Enable]	
		++: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit



## ☞ **COM1/COM2/Serial Port for Out-of Band Management / Windows Emergency Management Service (EMS)**

### ☞ **Console Redirection** (Note)

Select whether to enable console redirection for specified device. Console redirection enables users to manage the system from a remote location.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### ☞ **Console Redirection Settings**

#### ☞ **Terminal Type**

Select a terminal type to be used for console redirection.

Options available: VT100/VT100+/ANSI /VT-UTF8.

#### ☞ **Bits per second**

Select the baud rate for console redirection.

Options available: 9600/19200/57600/115200.

#### ☞ **Data Bits**

Select the data bits for console redirection.

Options available: 7/8.

#### ☞ **Parity**

A parity bit can be sent with the data bits to detect some transmission errors.

Even: parity bit is 0 if the num of 1's in the data bits is even.

Odd: parity bit is 0 if num of 1's the data bits is odd.

Mark: parity bit is always 1. Space: Parity bit is always 0.

(Note) Advanced items prompt when this item is defined.

Mark and Space Parity do not allow for error detection.

Options available: None/Even/Odd/Mark/Space.

#### **Stop Bits**

Stop bits indicate the end of a serial data packet. (A start bit indicates the beginning). The standard setting is 1 stop bit. Communication with slow devices may require more than 1 stop bit.

Options available: 1/2.

#### **Flow Control**

Flow control can prevent data loss from buffer overflow. When sending data, if the receiving buffers are full, a 'stop' signal can be sent to stop the data flow. Once the buffers are empty, a 'start' signal can be sent to re-start the flow. Hardware flow control uses two wires to send start/stop signals.

Options available: None/Hardware RTS/CTS.

#### **VT-UTF8 Combo Key Support** <sup>(Note)</sup>

Enable/Disable VT-UTF8 Combo Key Support.

Options available: Enabled/Disabled. Default setting is **Enabled**.

#### **Recorder Mode** <sup>(Note)</sup>

When this mode enabled, only text will be send. This is to capture Terminal data.

Options available: Enabled/Disabled.

#### **Resolution 100x31** <sup>(Note)</sup>

Enables or disables extended terminal resolution.

Options available: Enabled/Disabled.

#### **Legacy OS Redirection Resolution** <sup>(Note)</sup>

On Legacy OS, the number of Rows and Columns supported redirection.

Options available: 80x24/80X25.

#### **Putty KeyPad** <sup>(Note)</sup>

Select function FunctionKey and KeyPad on Putty.

Options available: VT100/LINUX/XTERMR6/SCO/ESCN/VT400.

#### **Redirection After BIOS POST** <sup>(Note)</sup>

This option allows user to enable console redirection after O.S has loaded.

Options available: Always Enable/Boot Loader. Default setting is **Always Enable**.

#### **Out-of-Bnad Mgmt Port**

Microsoft Windows Emergency Management Service (EMS) allows for remote management of a Windows Server OS through a serial port.

Options available: COM1/COM2.

#### **SOL Switch**

When enabled, COM1 Switch to AST2300 SOL UART.


When disabled, COM1 Switch to IT8728 SOL UART.

Options available: Enabled/Disabled. Default setting is **Disabled**.

---

(Note) The item is only available for COM1 and COM2.

## 2-2-10 Network Stack



### 🔑 Network stack

Enable/Disable UEFI network stack.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### 🔑 Ipv4 PXE Support<sup>(Note)</sup>

Enable/Disable Ipv4 PXE feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### 🔑 Ipv6 PXE Support<sup>(Note)</sup>

Enable/Disable Ipv6 PXE feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.


### 🔑 PXE Boot wait time<sup>(Note)</sup>

Press the numeric key to configure PXE boot wait time.

(Note) This item appears when **Network Stack** is set to **Enabled**.



## 2-2-11 Intel (R) 82574L Gigabit Network Connection



## ☞ **PORT CONFIGURATION MENU**

### ☞ **NIC Configuration**

Press [Enter] for configuration of advanced items.

### ☞ **Blink LEDs (range 0-15 seconds)**

Blink LEDs for the specified duration (up to 15 seconds).

Press the numeric keys to input the desired value.

## ☞ **PORT CONFIGURATION INFORMATION**

### ☞ **UEFI Driver**

Display the UEFI driver information.

### ☞ **Adapter PBA**

Display the Adapter PBA information.

### ☞ **Chip Type**

Display the Chip type.

### ☞ **PCI Device ID**

Display the PCI device ID.

### ☞ **Bus:Device:Function**

Display the number of Bus/Device/Function

### ☞ **Link Status**

Display the link status.

### ☞ **MAC Address**

Display the Factory MAC address information.

### ☞ **Virtual MAC Address**

Display the virtual MAC address information.

### ☞ **Link Speed**

Change link speed duplex for current port.

Options available: AutoNeg/10Mbps Half/10Mbps Half/10Mbps Half/100Mbps Full.

Default setting is **AutoNeg**.

### ☞ **Wake On LAN**

Enable/Disable Wake On LAN feature.



Options available: Enabled/Disabled. Default setting is **Enabled**.

## 2-3 Chipset Menu

The Chipset menu display submenu options for configuring the function of North Bridge and South Bridge. Select a submenu item, then press Enter to access the related submenu screen.



## 2-3-1 North Bridge



## ☞ IOH Configuration

Press [Enter] for configuration of advanced items.

## ☞ QPI Configuration

Press [Enter] for configuration of advanced items.

## ☞ Compatibility RID

Enable/Disable Compatibility RID function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

## ☞ Memory Configuration

### ☞ Total Memory

Displays the total capacity of the installed memory.

### ☞ Current Memory Mode

Displays the current memory mode. Memory mode can be determined in **Memory Mode** item.

### ☞ Current Memory Speed

Displays the current memory speed.

### ☞ Mirroring/Sparing

Displays the current support memory mode.

### ☞ Memory Mode

Determine the memory mode.

When set to Independent mode, all DIMMs are available to the operation system.

When set to Mirroring mode, the motherboard maintains two identical (redundant) copies of all data in memory.

When set to Lockstep mode, the motherboard uses two areas of memory to run the same set of operations in parallel.

When set to Sparing mode, a preset threshold of correctable errors is used to trigger fail-over.

The spare memory is put online and used as active memory in place of the failed memory.

Options available: Independent /Mirroring/Lockstep/Sparing.

### ☞ DDR Speed

Configure the DDR Speed.

Options available: Auto/Force DDR3 800/Force DDR3 1066/Force DDR3 1333/Force DDR3 1600/Force DDR3 1866. Default setting is **Auto**.

### ☞ Channel interleaving

Configure DDR Channel Interleaving.

Options available: Auto/1 Way/2 Way/3 Way/4 Way. Default setting is **Auto**.

### ☞ Rank interleaving

Configure DDR Rank Interleaving. This improves memory performance by masking the refresh cycles of each memory bank. The Rank Interleaving works between different physical banks.

Options available: Auto/1 Way/2 Way/3 Way/4 Way. Default setting is **Auto**.

### ☞ Patrol Scrub

Enable/Disable Patrol Scrub function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### ☞ Demand Scrub

Enable/Disable Demand Scrub function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### **Device Tagging**

Enable/Disable Device Tagging function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### **Rank Margin**

Enable/Disable Rank Margin function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### **Thermal Thortting**

Configure theThermal Thortting.

Options available: Disabled/OLTT/CLTT. Default setting is **CLTT**.

### **OLTT Peak BW %**

Press the numeric keys to increase or decrease the desired values.

### **Altitude**

Configure the Altitude value.


Options available: Auto/300 M/900 M/1500 M/3000 M. Default setting is **300 M**.

### **Enforce DIMM**

To enforce POR function. When disabled, the system will enforce 1600MHz LRDIMM.

Options available: Enforce EN/Stretch EN/Enforce DIS. Default setting is **Enforce Dis**.


## 2-3-1-1 IOH Configuration



- ☞ **IOH Configuration**
- ☞ **Intel(R) VT for Directed I/O Configuration**  
Press [Enter] for configuration of advanced items.
- ☞ **Intel(R) I/OAT (Intel I/O Acceleration Technology)**  
Enable/Disable Intel I/OAT function.  
Options available: Enabled/Disabled. Default setting is **Disabled**.
- ☞ **DCA Support (Direct Cache Access)**  
Enable/Disable Intel DCA Support function.  
Options available: Enabled/Disabled. Default setting is **Enabled**.
- ☞ **VGA Priority**  
Define the display device priority.  
Options available: Onboard/Offboard. Default setting is **Offboard**.
- ☞ **Gen3 Equalization WA's**  
Enable/Disable the support for Gen3 Equalization Workaround.  
Options available: Enabled/Disabled. Default setting is **Disabled**.
- ☞ **IOH Resource Seletion Type**  
Configure IOH Resource Seletion Type.  
Options available: Auto/Manual. Default setting is **Auto**.
- ☞ **No Snoop Optimization**  
Options VC0/VCP/VC1. Default setting is **VC1**.
- ☞ **MMIOH Size (Size of the Memory Mapped Configuration Space)**  
Options available: 1G/2G/4G/8G/16G/32G/64G. Default setting is **64G**.
- ☞ **MMCFG BASE (Base address of the Memory Mapped Configuration Space)**  
Options available: 0x80000000/0xA0000000/0xC0000000/0x40000000. Default setting is **0x80000000**.
- ☞ **Intel(R) VT-d**  
Enable/Disable Intel VT-d Technology function.  
Options available: Enabled/Disabled. Default setting is **Enabled**.



## 2-3-1-2 QPI Configuration



### 🔑 Current QPI Link Speed/ Current QPI Link Freq

Displays the current QPI Link Speed and Frequency information.

### 🔑 Isoc

Enable/Disable Isoc.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### 🔑 MesegEn

Options available: Enabled/Disabled. Default setting is **Disabled**.

### 🔑 QPI Link Speed Mode

Configure QPI Link Speed mode.

Options available: Fast/Slow. Default setting is **Fast**.

### 🔑 QPI Link Frequency Select

Configure QPI Link Frequency.

Options available: Auto/6.4 GT/s/7.2 GT/s/8.6 GT/s. Default setting is **Auto**.

### 🔑 QPI Link0s

Options available: Enabled/Disabled. Default setting is **Disabled**.

### 🔑 QPI Link0p

Options available: Enabled/Disabled. Default setting is **Disabled**.


### 🔑 QPI Link1

Options available: Enabled/Disabled. Default setting is **Enabled**.

### 🔑 Snoop Mode

Options available: Auto/Disabled. Default setting is **Auto**.

### 2-3-1-3 DIMM Information



#### ☞ CPU Socket 0 DIMM Information

#### ☞ CPU Socket 0:

#### ☞ DDR3\_P0\_A0/DDR3\_P0\_A1/DDR3\_P0\_B0/DDR3\_P0\_B1 Status

#### ☞ DDR3\_P0\_C0/DDR3\_P0\_C1/DDR3\_P0\_D0/DDR3\_P0\_D1 Status

The size of memory installed on each of the DDR3 slots.

## 2-3-2 South Bridge Configuration



### ☞ PCH Information

### ☞ Name/Stepping Information

Displays the name and stepping information of the south bridge.

### ☞ SB Chipset Configuration

### ☞ PCH Compatibility RID

Enable/Disable PCH Compatibility RID support.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### ☞ Restore on AC Power Loss

Defines the power state to resume to after a system shutdown that is due to an interruption in AC power.

When set to Last State, the system will return to the active power state prior to shutdown. When set to Stay Off, the system remains off after power shutdown.

Options available: Last State/Stay Off/Power On. The default setting depends on the BMC setting.

### ☞ SCU Devices

Enable/Disable Patsburg SCU device.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### ☞ High Precision Event Timer Configuration


### ☞ High Precision Event Timer

Enable/Disable High Precision Event Timer.

Options available: Enabled/Disabled. Default setting is **Enabled**.

(Note) When the power policy is controlled by BMC, please wait for 15-20 seconds for BMC to save the last power state.

## 2-3-3 Intel ME Subsystem



### Intel ME Subsystem Configuration


#### ME Subsystem

Enable/Disable ME subsystem configuration.

Options available: Enabled/Disabled. Default setting is **Enabled**.

## 2-4 Security Menu

The Security menu allows you to safeguard and protect the system from unauthorized use by setting up access passwords.



There are two types of passwords that you can set:

- Administrator Password

Entering this password will allow the user to access and change all settings in the Setup Utility.

- User Password

Entering this password will restrict a user's access to the Setup menus. To enable or disable this field, a Administrator Password must first be set. A user can only access and modify the System Time, System Date, and Set User Password fields.

### ⚙ Administrator Password


Press Enter to configure the Administrator password.

### ⚙ User Password

Press Enter to configure the user password.

## 2-5 Boot Menu

The Boot menu allows you to set the drive priority during system boot-up. BIOS setup will display an error message if the legacy drive(s) specified is not bootable.



### 🔑 Boot Configuration

### 🔑 Setup Prompt Timeout

Number of seconds to wait for setup activation key. 65535(0xFFFF) means indefinite waiting."

Press the numeric keys to input the desired value.

### 🔑 Bootup NumLock State

Enable or Disable Bootup NumLock function.

Options available: On/Off. Default setting is **On**.

### 🔑 Quiet Boot

Enables or disables showing the logo during POST.

Options available: Enabled/Disabled. Default setting is **Enabled**.

### 🔑 Fast Boot

If enabled, the BIOS will shorten the booting process by skipping some tests and shortening others.

Options available: Enabled/Disabled. Default setting is **Disabled**.

### 🔑 Boot Priority Order

### 🔑 Boot Option #1/#2/#3/#4

Press Enter to configure the boot priority.

By default, the server searches for boot devices in the following sequence:

1. UEFI device.
2. Hard drive.
3. Network device.
4. Removable device

☞ **Hard Drive BBS Priorities**

Press Enter to configure the boot priority.

☞ **Network Device BBS Priorities**

Press Enter to configure the boot priority.

☞ **CSM16 Parameters**

Press Enter to configure the CSM16 parameters.

☞ **CSM Parameters**

Press Enter to configure the CSM parameters.

## 2-5-1 CSM16 Parameters



### CSM16 Parameters

#### CSM16 Module Version

Display CSM Module version information.

#### Gate20 Active

Upon Request: GA20 can be disabled using BIOS services.

Always: Do not allow disabling GA20; this option is useful when any RT code is executed above 1MB.

Options available: Upon Request/Always. Default setting is **Upon Request**.

#### Option ROM Messages

Option ROM Messages.

Options available: Force BIOS/Keep Current. Default setting is **Force BIOS**.

#### INT19 Endless Retry

Enabled: Allowed headless retry boot

Options available: Enabled/Disabled. Default setting is **Disabled**.

#### INT19 Trap Response

BIOS reaction on INT19 trapping by Option ROM


Immediate: execute the trap right away.

Postpone: execute the trap during legacy boot.

Options available: Immediate/Postpone. Default setting is **Immediate**.



## 2-5-2 CSM Parameters



### CSM parameters

Press Enter to configure the advanced items.

### Launch CSM (Compatibility Support Module)

Enable/Disable Compatibility Support Module (CSM) launch.

Options available: Enabled/Disabled. Default setting is **Enabled**.



- The following five items appear and are configurable when the **Launch CSM** is set to **Enabled**.
- If the **Launch CSM** is set to **Disabled**, the following five items will not be able to support Legacy mode.

### Boot option filter

Determines which devices system will boot to.

Options available: UEFI and Legacy/Legacy only/UEFI only. Default setting is **UEFI and Legacy**.

### Launch PXE OpROM policy

Determines which devices system will boot to.

Options available: Do not launch/UEFI only/Legacy only/Legacy first/UEFI first. Default setting is **Legacy only**.

### Launch Storage OpROM policy

Determines which devices system will boot to.

Options available: Do not launch/UEFI only/Legacy only/Legacy first/UEFI first. Default setting is **Legacy only**.

### Launch Video OpROM policy

Determines which devices system will boot to.


Options available: Do not launch/UEFI only/Legacy only/Legacy first/UEFI first. Default setting is **Legacy only**.

### **Other PCI device ROM priority**

For PCI devices other than Network, Mass storage or Video device, defines which OpROM to launch.  
Options available: UEFI OpROM/Legacy OpROM. Default setting is **UEFI OpROM**.

## 2-6 Exit Menu

The Exit menu displays the various options to quit from the BIOS setup. Highlight any of the exit options then press **Enter**.



### **Save Changes and Exit**

Saves changes made and close the BIOS setup.

Options available: Yes/No.

### **Discard Changes and Exit**

Discards changes made and close the BIOS setup.

Options available: Yes/No.

### **Save Options**

### **Save Changes**

Saves changes made in the BIOS setup.

Options available: Yes/No.

### **Restore Defaults**

Loads the default settings for all BIOS setup parameters. Setup Defaults are quite demanding in terms of resources consumption. If you are using low-speed memory chips or other kinds of low-performance components and you choose to load these settings, the system might not function properly.

Options available: Yes/No.

### **Boot Override**

Press Enter to configure the device as the boot-up drive.

### **UEFI: Built-in in EFI Shell**

Press <Enter> on this item to Launch EFI Shell from filesystem device.


## 2-7 BIOS Recovery Instruction

The system has an embedded recovery technique. In the event that the BIOS becomes corrupt the boot block can be used to restore the BIOS to a working state. To restore your BIOS, please follow the instructions listed below:


### Recovery Instruction:

1. Change xxx.ROM to amiboot.rom.
2. Copy amiboot.rom and AFUDOS.exe to USB diskette.
3. Setting BIOS Recovery jump to enabled status.

### BIOS Recovery Jumper



4. Boot into BIOS recovery.
5. Run Proceed with flash update.
6. BIOS update.



## Chapter 3 Appendix

### 3-1 Regulatory Statements

#### **Regulatory Notices**

This document must not be copied without our written permission, and the contents there of must not be imparted to a third party nor be used for any unauthorized purpose. Contravention will be prosecuted. We believe that the information contained herein was accurate in all respects at the time of printing. GIGABYTE cannot, however, assume any responsibility for errors or omissions in this text. Also note that the information in this document is subject to change without notice and should not be construed as a commitment by GIGABYTE.

#### **Our Commitment to Preserving the Environment**

In addition to high-efficiency performance, all GIGABYTE motherboards fulfill European Union regulations for RoHS (Restriction of Certain Hazardous Substances in Electrical and Electronic Equipment) and WEEE (Waste Electrical and Electronic Equipment) environmental directives, as well as most major worldwide safety requirements. To prevent releases of harmful substances into the environment and to maximize the use of our natural resources, GIGABYTE provides the following information on how you can responsibly recycle or reuse most of the materials in your "end of life" product.

#### **Restriction of Hazardous Substances (RoHS) Directive Statement**

GIGABYTE products have not intended to add and safe from hazardous substances (Cd, Pb, Hg, Cr+6, PBDE and PBB). The parts and components have been carefully selected to meet RoHS requirement. Moreover, we at GIGABYTE are continuing our efforts to develop products that do not use internationally banned toxic chemicals.

#### **Waste Electrical & Electronic Equipment (WEEE) Directive Statement**

GIGABYTE will fulfill the national laws as interpreted from the 2002/96/EC WEEE (Waste Electrical and Electronic Equipment) directive. The WEEE Directive specifies the treatment, collection, recycling and disposal of electric and electronic devices and their components. Under the Directive, used equipment must be marked, collected separately, and disposed of properly.

#### **WEEE Symbol Statement**



The symbol shown below is on the product or on its packaging, which indicates that this product must not be disposed of with other waste. Instead, the device should be taken to the waste collection centers for activation of the treatment, collection, recycling and disposal procedure.

The separate collection and recycling of your waste equipment at the time of disposal will help to conserve natural resources and ensure that it is recycled in a manner that protects human health and the environment. For more information about where you can drop off your waste equipment for recycling, please contact your local government office, your household waste disposal service or where you purchased the product for details of environmentally safe recycling.

- ♦ When your electrical or electronic equipment is no longer useful to you, "take it back" to your local or regional waste collection administration for recycling.
- ♦ If you need further assistance in recycling, reusing in your "end of life" product, you may contact us at the Customer Care number listed in your product's user's manual and we will be glad to help you with your effort.

Finally, we suggest that you practice other environmentally friendly actions by understanding and using the energy-saving features of this product (where applicable), recycling the inner and outer packaging (including shipping containers) this product was delivered in, and by disposing of or recycling used batteries properly. With your help, we can reduce the amount of natural resources needed to produce electrical and electronic equipment, minimize the use of landfills for the disposal of "end of life" products, and generally improve our quality of life by ensuring that potentially hazardous substances are not released into the environment and are disposed of properly.